

**LESSON 21 AN/FCC-100(V) 7 & 9X PROGRAMMING PORT 5
 CDI EQUIRATE 2400 BPS CONFIGURATION
 EXAMPLE OF AN AUTODIN CIRCUIT**

STEP	OPERATOR ACTION	MESSAGE DISPLAYED	SELECT
1	Press the RESTART key.		
2	Press the NEXT ENTRY P key.	ACTIVATE	
3	Press the NEXT ENTRY P key.	EXAMINE	
4	Press the NEXT ENTRY P key. (Select CONFIGURE using the DOWN B arrow key).	CONFIGURE	CONFIGURE
5	Select OFFLINE using the DOWN B arrow key.	OFFLINE	OFFLINE
6	Select A-CONFIG using the DOWN B arrow key.	A-CONFIG	A-CONFIG
7	If selection displayed is not PORT 5 , then scroll through the options by pressing the NEXT ENTRY P key until PORT 5 is displayed. (Select PORT 5 using the DOWN B arrow key).	SYSTEM PORT 5	PORT 5
8	If selection displayed is not CDI , then scroll through the options by pressing the NEXT ENTRY P key until CDI is displayed. (Select CDI using the DOWN B arrow key).	CDI	CDI
9	If selection displayed is not EQUIRATE then scroll through the options by pressing the NEXT ENTRY P key until EQUIRATE is displayed. (Select EQUIRATE using the DOWN B arrow key).	EQUIRATE	EQUIRATE
10	If selection displayed is not 2400 then scroll through the options by pressing the NEXT ENTRY P key until 2400 is displayed. (Select 2400 using the DOWN B arrow key).	XXX 75 TO 96K	2400

**LESSON 21 AN/FCC-100(V) 7 & 9X PROGRAMMING PORT 5
 CDI EQUIRATE 2400 BPS CONFIGURATION
 EXAMPLE OF AN AUTODIN CIRCUIT**

STEP	OPERATOR ACTION	MESSAGE DISPLAYED	SELECT
11	If selection displayed is not CL-HIGH then scroll through the options by pressing the NEXT ENTRY P key until CL-HIGH is displayed. (Select CL-HIGH using the DOWN B arrow key).	CL-HIGH CL-RTS-DCD CL-DTR-CTS	CL-HIGH
12	Press the STORE to "save this CDI PORT 5 CONFIGURATION into the OFFLINE A-CONFIG memory.	CDI	

**END OF AN/FCC-100(V)7 & 9X PORT 5 CDI
 EQUIRATE 2400 BPS POWER CONFIGURATION
 EXAMPLE OF AN AUTODIN CIRCUIT**